SAMSUNG

GSM TELEPHONE

SM-T805

SERVICE Manual

GSM TELEPHONE



CONTENTS

1. Safety Precautions
2. Specification
3. Product Function
4. Exploded View and Parts list
5. MAIN Electrical Parts List
6. Level 1 Repair
7. Level 2 Repair
8. Level 3 Repair
9. Reference data

Notice: All functionality, features, specifications, and other product information provided in this document, including but not limited to, benefits, design, pricing, components, performance, availability, and capabiliti -es of the product are subject to change without notice. Samsung reserves the right to alter this doc -ument or the product described herein at anytime, without obligation to provide notification of such changes.

1. Safety Precautions

1-1. Repair Precaution

Before attempting any repair or detailed tuning, shield the device from RF noise or static electricity discharges.

Use only demagnetized tools that are specifically designed for small electronic repairs, as most electronic parts are sensitive to electromagnetic forces.

Use only high quality screwdrivers when servicing products. Low quality screwdrivers can easily damage the heads of screws.

Use only conductor wire of the properly gauge and insulation for low resistance, because of the low margin of error of most testing equipment.
We recommend 22-gauge twisted copper wire.

Hand-soldering is not recommended, because printed circuit boards (PCBs) can be easily damaged, even with relatively low heat. Never use a soldering iron with a power rating of more than 100 watts and use only lead-free solder with a melting point below 250°C (482°F).

Prior to disassembling the battery charger for repair, ensure that the AC power is disconnected. Always use the replacement parts that are registered in the SEC system. Third-party replac ement parts may not function properly.

Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

1-2. ESD(Electrostatically Sensitive Devices) Precaution

Many semiconductors and ESDs in electronic devices are particularly sensitive to static discha rge and can be easily damaged by it. We recommend protecting these components with cond uctive anti-static bags when you store or transport them.

Always use an anti-static strap or wristband and remove electrostatic buildup or dissipate static electricity from your body before repairing ESDs.

Ensure that soldering irons have AC adapter with ground wires and that the ground wires are properly connected.

Use only desoldering tools with plastic tips to prevent static discharge.

Properly shield the work environment from accidental electrostatic discharge before opening packages containing ESDs.

The potential for static electricity discharge may be increased in low humidity environments, such as air-conditioned rooms. Increase the airflow to the working area to decrease the chance of accidental static electricity discharges.

Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

2. Specification

2-1. GSM General Specification

	GSM850	EGSM 900	DCS1800	PCS1900	WCDMA 2100	WCDMA 900	WCMDA 850	WCDMA 1900
Freq. Band[MHz] Uplink/ Downlink	824~849 869~894	880~915 925~960	1710~1785 1805~1880	1850~1910 1930~1990	1922~1977 2112~2167	880~915 925~960	824~849 869~894	1852~1907 1932~1987
ARFCN range	128~251	0~124 & 975~1023	512~885	512~810	UL: 9612~9888 DL: 10562~10838	UL: 2712~2863 DL: 2937~3088	UL: 4132~4233 DL: 4357~4458	UL: 9612~9888 DL: 10562~10838
Tx/Rx spacing	45MHz	45MHz	95MHz	80MHz	190MHz	45MHz	45MHz	80MHz
Mod. Bit rate/ Bit Period	270.833kbps 3.692us	270.833kbps 3.692us	270.833kbps 3.692us	270.833kbps 3.692us	3.84Mcps	3.84Mcps	3.84Mcps	3.84Mcps
Time Slot Period/ Frame Period	576.9us 4.615ms	576.9us 4.615ms	576.9us 4.615ms	576.9us 4.615ms	FrameLength: 10ms Slotlength: 0.667ms	FrameLength: 10ms Slotlength: 0.667ms	FrameLength: 10ms Slotlength: 0.667ms	FrameLength: 10ms Slotlength: 0.667ms
Modulation	0.3GMSK	0.3GMSK	0.3GMSK	0.3GMSK	QPSKHQPSK	QPSKHQPSK	QPSKHQPSK	QPSKHQPSK
MS Power	33dBm~5dBm	33dBm~5dBm	30dBm~0dBm	30dBm~0dBm	24dBm~ -50dBm	24dBm~ -50dBm	24dBm~ -50dBm	24dBm~ -50dBm
Power Class	5pcl ~ 19pcl	5pcl ~ 19pcl	0pcl ~ 15pcl	0pcl ~ 15pcl	3(max+24dBm)	3(max+24dBm)	3(max+24dBm)	3(max+24dBm)
Sensitivity	-102dBm	-102dBm	-100dBm	-100dBm	-106.7dBm	-103.7dBm	-104.7dBm	-104.7dBm
TDMA Mux	8	8	8	8	–	-	-	-
Cell Radius	35Km	35Km	2Km	2Km	2Km	2Km	2Km	2Km

Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

2-2. GSM Tx Power Class

TX Power control level	GSM850
5	33±2 dBm
6	31±2 dBm
7	29±2 dBm
8	27±2 dBm
9	25±2 dBm
10	23±2 dBm
11	21±2 dBm
12	19±2 dBm
13	17±2 dBm
14	15±2 dBm
15	13±2 dBm
16	11±3 dBm
17	9±3dBm
18	7±3 dBm
19	5±3 dBm

TX Power control level	EGSM900
5	33±2 dBm
6	31±2 dBm
7	29±2 dBm
8	27±2 dBm
9	25±2 dBm
10	23±2 dBm
11	21±2 dBm
12	19±2 dBm
13	17±2 dBm
14	15±2 dBm
15	13±2 dBm
16	11±3 dBm
17	9±3dBm
18	7±3 dBm
19	5±3 dBm

TX Power control level	DCS1800
0	30±3 dBm
1	28±3 dBm
2	26±3 dBm
3	24±3 dBm
4	22±3 dBm
5	20±3 dBm
6	18±3 dBm
7	16±3 dBm
8	14±3 dBm
9	12±4 dBm
10	10±4 dBm
11	8±4 dBm
12	6±4 dBm
13	4±4 dBm
14	2±5 dBm
15	0±5 dBm

TX Power control level	PCS1900
0	30±3 dBm
1	28±3 dBm
2	26±3 dBm
3	24±3 dBm
4	22±3 dBm
5	20±3 dBm
6	18±3 dBm
7	16±3 dBm
8	14±3 dBm
9	12±4 dBm
10	10±4 dBm
11	8±4 dBm
12	6±4 dBm
13	4±4 dBm
14	2±5 dBm
15	0±5 dBm

Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

2-3. LTE General Specification

	LTE Band1	LTE Band3	LTE Band5	LTE Band7	LTE Band8	LTE Band20
Freq. Band[MHz] Uplink/ Downlink	1920~1980 2110~2170	1710~1785 1805~1880	824~849 869~894	2500~2570 1805~1880	880~914.9 925~959.9	832~862 791~821
ARFCN range	UL: 18000~18599 DL: 0~599	UL: 19200~19950 DL: 1805~1880	UL: 20400~20649 DL: 2400~2649	UL: 2500~2570 DL: 2620~2690	UL: 21450-21799 DL: 3450-3799	UL: 24150~24450 DL: 6150~6450
Tx/Rx spacing	190MHz	95MHz	45MHz	120MHz	45MHZ	41MHz
Channel Bandwidth	5/10/15/20 MHz	1.4/3/5/10/15/20 MHz	1.4/3/5/10 MHz	5/10/15/20 MHz	1.4/3/5/10MHz	5/10/15/20 MHz
Modulation	QPSK,16/64QAM	QPSK,16/64QAM	QPSK,16/64QAM	QPSK,16/64QAM	QPSK,16/64QAM	QPSK,16/64QAM
MS Power (MPR)	-35~25.7 dBm	-35~25.7 dBm	-35~25.7 dBm	-35~25.7 dBm	-35~25.7 dBm	-35~25.7 dBm
Sensitivit (QPSK) (BW 10MHz)	-94 dBm	-92 dBm	-92 dBm	-95dBm	-95dBm	-94dBm
Cell Radius	>5Km	>5Km	>5Km	>5Km	>5Km	>5Km

Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

3. Operation Instruction and Installation

Main Function

- Android OS: KitKat (4.4)
- 10.5" WQXGA On-Cell Touch AMOLED (OCTA)
- A-GPS / GLONASS / BT v4.0 + EDR with LE / USB v2.0 / Wi-Fi (802.11 a/b/g/n/ac VHT80) / MHL 2.1 / OTG
- Main 8.0 MP, Sub 2.0 MP
- Recording definition: 1080p
- Sensors: Accelerometer, Gyro, Geomagnetic, Light Sensor, Fingerprint
- Additional :
  - Octa core AP (1.9 GHz Quad Core / 1.3GHz Quad Core)
  - CP (LTE baseband controller)

Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

4. Exploded View and Parts List

4-1. Cellular phone Exploded View



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

5. MAIN Electrical Parts List

SEC CODE	Design Location	Description
0403-001688	ZD500	DIODE-ZENER
0403-001688	ZD700	DIODE-ZENER
0404-001250	D501	DIODE-SCHOTTKY
0404-001782	D500	DIODE-SCHOTTKY
0404-001782	D502	DIODE-SCHOTTKY
0406-001223	ZD711	DIODE-TVS
0406-001223	ZD712	DIODE-TVS
0406-001375	ZD501	DIODE-TVS
0406-001375	ZD502	DIODE-TVS
0406-001413	ZD702	DIODE-TVS
0406-001413	ZD703	DIODE-TVS
0406-001413	ZD709	DIODE-TVS
0406-001413	ZD710	DIODE-TVS
0406-001413	ZD716	DIODE-TVS
0406-001413	ZD717	DIODE-TVS
0406-001413	ZD718	DIODE-TVS
0406-001459	ZD701	DIODE-TVS
0406-001494	ZD606	DIODE-TVS
0406-001494	ZD607	DIODE-TVS
0406-001494	ZD608	DIODE-TVS
0406-001494	ZD611	DIODE-TVS
0406-001494	ZD613	DIODE-TVS
0406-001494	ZD614	DIODE-TVS
0406-001494	ZD615	DIODE-TVS
0406-001494	ZD616	DIODE-TVS
0406-001494	ZD707	DIODE-TVS
0406-001494	ZD800	DIODE-TVS
0406-001494	ZD801	DIODE-TVS
0406-001494	ZD802	DIODE-TVS
0406-001494	ZD803	DIODE-TVS
0406-001494	ZD804	DIODE-TVS
0406-001494	ZD807	DIODE-TVS
0406-001505	ZD600	DIODE-TVS
0406-001505	ZD601	DIODE-TVS
0406-001505	ZD602	DIODE-TVS
0406-001505	ZD603	DIODE-TVS
0406-001505	ZD604	DIODE-TVS
0406-001505	ZD605	DIODE-TVS
0406-001505	ZD708	DIODE-TVS
0406-001505	ZD713	DIODE-TVS
0406-001505	ZD714	DIODE-TVS
0406-001505	ZD715	DIODE-TVS

Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

0406-001506	ZD720	DIODE-TVS
0406-001506	ZD721	DIODE-TVS
0406-001549	ZD704	DIODE-TVS
0406-001549	ZD705	DIODE-TVS
0505-002088	TR500	FET-SILICON
0505-002088	TR501	FET-SILICON
0505-002341	TR503	FET-SILICON
0505-002341	TR701	FET-SILICON
0505-002384	TR900	FET-SILICON
0505-002720	U700	FET-SILICON
0505-003070	TR700	FET-SILICON
0505-003234	TR600	FET-SILICON
0505-003234	TR601	FET-SILICON
0601-003398	LED500	LED
0801-003228	U508	IC-CMOS LOGIC
0801-003228	U509	IC-CMOS LOGIC
0801-003228	U510	IC-CMOS LOGIC
0801-003437	U1010	IC-CMOS LOGIC
0902-003074	UCP4001	IC-MICROPROCESSOR
1001-001394	U506	IC-ANALOG SWITCH
1107-002297	UME4000	IC-EMMC
1201-003642	PAM1002	IC-POWER AMP
1201-003645	PAM1001	IC-POWER AMP
1201-003729	U201	IC-GPS AMP
1202-001120	U600	IC-VOLTAGE COMP.
1203-002250	U504	IC-VOL. DETECTOR
1203-004776	U505	IC-POSI.FIXED REG.
1203-006182	U702	IC-VOL. DETECTOR
1203-006766	U203	IC-VOL. DETECTOR
1203-006766	U302	IC-VOL. DETECTOR
1203-006767	U903	IC-MULTI REG.
1203-007766	U1003	IC-DC/DC CONVERTER
1203-007791	U800	IC-POSI.FIXED REG.
1203-007791	U801	IC-POSI.FIXED REG.
1203-007823	U802	IC-DC/DC CONVERTER
1203-008004	U701	IC-VOL. DETECTOR
1203-008158	U502	IC-POWER SUPERVISOR
1203-008172	U500	IC-SWITCH REG.
1203-008193	U512	IC-POWER SUPERVISOR
1203-008217	U805	IC-DC/DC CONVERTER
1205-004753	U804	IC-TRANSMITTER
1205-004772	U602	IC-CODEC
1205-004863	UCP301	IC-MODEM

Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

1205-004884	U1007	IC-TRANSMITTER
1205-004916	U904	IC-SWITCH
1205-005012	U206	IC-WIFI
1205-005016	U202	IC-GPS RECEIVER
1209-002245	U902	IC-SENSOR
1209-002246	U901	IC-SENSOR
1209-002252	U1009	IC-SENSOR
1301-002167	U900	IC-FPGA
1404-001694	TH4000	THERMISTOR-NTC
1404-001694	TH4001	THERMISTOR-NTC
1404-001694	TH4002	THERMISTOR-NTC
1404-001728	TH301	THERMISTOR-NTC
1405-001375	V1001	VARISTOR
2007-000148	R617	R-CHIP
2007-000148	R618	R-CHIP
2007-000148	R619	R-CHIP
2007-000169	R1005	R-CHIP
2007-000174	R904	R-CHIP
2007-000174	R905	R-CHIP
2007-000174	R906	R-CHIP
2007-000174	R907	R-CHIP
2007-000174	R908	R-CHIP
2007-000174	R909	R-CHIP
2007-000174	R910	R-CHIP
2007-000174	R911	R-CHIP
2007-000174	R912	R-CHIP
2007-000174	R913	R-CHIP
2007-001308	R4082	R-CHIP
2007-001308	R4109	R-CHIP
2007-001325	R613	R-CHIP
2007-001325	R614	R-CHIP
2007-003015	R502	R-CHIP
2007-007107	R314	R-CHIP
2007-007136	R4087	R-CHIP
2007-007136	R4088	R-CHIP
2007-007139	R807	R-CHIP
2007-007142	R514	R-CHIP
2007-007312	R4051	R-CHIP
2007-007312	R4054	R-CHIP
2007-007312	R4067	R-CHIP
2007-007312	R4071	R-CHIP
2007-007312	R4098	R-CHIP
2007-007312	R4099	R-CHIP

Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

2007-007312	R4100	R-CHIP
2007-007312	R4102	R-CHIP
2007-007318	R1025	R-CHIP
2007-007517	R4072	R-CHIP
2007-007517	R4073	R-CHIP
2007-007517	R4080	R-CHIP
2007-007517	R4081	R-CHIP
2007-007517	R4096	R-CHIP
2007-007517	R4097	R-CHIP
2007-007585	R202	R-CHIP
2007-007627	R919	R-CHIP
2007-007741	R4085	R-CHIP
2007-007741	R805	R-CHIP
2007-007942	R4008	R-CHIP
2007-007942	R4200	R-CHIP
2007-007946	R4201	R-CHIP
2007-008045	R511	R-CHIP
2007-008045	R525	R-CHIP
2007-008045	R707	R-CHIP
2007-008049	R710	R-CHIP
2007-008049	R719	R-CHIP
2007-008051	R705	R-CHIP
2007-008052	R4049	R-CHIP
2007-008052	R4050	R-CHIP
2007-008052	R4068	R-CHIP
2007-008052	R515	R-CHIP
2007-008052	R523	R-CHIP
2007-008052	R803	R-CHIP
2007-008052	R804	R-CHIP
2007-008052	R806	R-CHIP
2007-008052	R902	R-CHIP
2007-008052	R903	R-CHIP
2007-008055	R315	R-CHIP
2007-008055	R4031	R-CHIP
2007-008055	R4032	R-CHIP
2007-008055	R4034	R-CHIP
2007-008055	R4035	R-CHIP
2007-008055	R4036	R-CHIP
2007-008055	R4038	R-CHIP
2007-008055	R4084	R-CHIP
2007-008055	R700	R-CHIP
2007-008055	R711	R-CHIP
2007-008055	R724	R-CHIP

Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

2007-008057	R1002	R-CHIP
2007-008057	R1003	R-CHIP
2007-008403	R521	R-CHIP
2007-008419	R319	R-CHIP
2007-008419	R321	R-CHIP
2007-008419	R500	R-CHIP
2007-008419	R501	R-CHIP
2007-008420	R510	R-CHIP
2007-008420	R516	R-CHIP
2007-008420	R517	R-CHIP
2007-008420	R518	R-CHIP
2007-008420	R601	R-CHIP
2007-008420	R723	R-CHIP
2007-008478	R4015	R-CHIP
2007-008478	R4016	R-CHIP
2007-008483	R209	R-CHIP
2007-008483	R210	R-CHIP
2007-008483	R211	R-CHIP
2007-008483	R212	R-CHIP
2007-008483	R213	R-CHIP
2007-008483	R716	R-CHIP
2007-008483	R717	R-CHIP
2007-008483	R721	R-CHIP
2007-008483	R722	R-CHIP
2007-008486	R503	R-CHIP
2007-008486	R512	R-CHIP
2007-008486	R520	R-CHIP
2007-008516	R4001	R-CHIP
2007-008516	R4002	R-CHIP
2007-008516	R4003	R-CHIP
2007-008516	R4004	R-CHIP
2007-008516	R4022	R-CHIP
2007-008516	R4026	R-CHIP
2007-008516	R4027	R-CHIP
2007-008516	R4063	R-CHIP
2007-008516	R4086	R-CHIP
2007-008516	R4103	R-CHIP
2007-008516	R4104	R-CHIP
2007-008516	R4105	R-CHIP
2007-008516	R4106	R-CHIP
2007-008516	R4107	R-CHIP
2007-008516	R4108	R-CHIP
2007-008516	R4115	R-CHIP

Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

2007-008516	R513	R-CHIP
2007-008516	R701	R-CHIP
2007-008516	R704	R-CHIP
2007-008516	R706	R-CHIP
2007-008516	R720	R-CHIP
2007-008516	R900	R-CHIP
2007-008516	R901	R-CHIP
2007-008516	R915	R-CHIP
2007-008516	R916	R-CHIP
2007-008531	R4064	R-CHIP
2007-008531	R4079	R-CHIP
2007-008579	R205	R-CHIP
2007-008588	R1019	R-CHIP
2007-008588	R1020	R-CHIP
2007-008588	R1021	R-CHIP
2007-008588	R1022	R-CHIP
2007-008588	R1023	R-CHIP
2007-008588	R307	R-CHIP
2007-008588	R308	R-CHIP
2007-008588	R309	R-CHIP
2007-008774	R702	R-CHIP
2007-008774	R708	R-CHIP
2007-008774	R709	R-CHIP
2007-008798	R508	R-CHIP
2007-008806	R1006	R-CHIP
2007-008806	R1024	R-CHIP
2007-008808	R201	R-CHIP
2007-009084	R504	R-CHIP
2007-009084	R522	R-CHIP
2007-009084	R603	R-CHIP
2007-009084	R616	R-CHIP
2007-009084	R703	R-CHIP
2007-009084	R715	R-CHIP
2007-009111	R4069	R-CHIP
2007-009155	R316	R-CHIP
2007-009155	R726	R-CHIP
2007-009157	R4074	R-CHIP
2007-009157	R4075	R-CHIP
2007-009157	R4076	R-CHIP
2007-009157	R4077	R-CHIP
2007-009157	R4078	R-CHIP
2007-009157	R4089	R-CHIP
2007-009157	R4090	R-CHIP

Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

2007-009157	R4091	R-CHIP
2007-009157	R4092	R-CHIP
2007-009157	R4093	R-CHIP
2007-009157	R4094	R-CHIP
2007-009157	R4095	R-CHIP
2007-009157	R918	R-CHIP
2007-009171	R4053	R-CHIP
2007-009171	R4055	R-CHIP
2007-009171	R4056	R-CHIP
2007-009171	R4057	R-CHIP
2007-009171	R4058	R-CHIP
2007-009171	R4059	R-CHIP
2007-009171	R4060	R-CHIP
2007-009171	R4061	R-CHIP
2007-009171	R4062	R-CHIP
2007-009171	R4112	R-CHIP
2007-009171	R4113	R-CHIP
2007-009199	R1001	R-CHIP
2007-009199	R313	R-CHIP
2007-009212	R604	R-CHIP
2007-009223	R602	R-CHIP
2007-009233	R324	R-CHIP
2007-009361	R1004	R-CHIP
2007-009408	R4009	R-CHIP
2007-009408	R4010	R-CHIP
2007-009408	R4011	R-CHIP
2007-009408	R4012	R-CHIP
2007-009408	R4013	R-CHIP
2007-009408	R4014	R-CHIP
2007-009408	R4019	R-CHIP
2007-009408	R4020	R-CHIP
2007-009408	R4039	R-CHIP
2007-009408	R4040	R-CHIP
2007-009408	R4041	R-CHIP
2007-009408	R4042	R-CHIP
2007-009408	R4043	R-CHIP
2007-009408	R4044	R-CHIP
2007-009408	R4118	R-CHIP
2007-009408	R4119	R-CHIP
2007-009801	R1017	R-CHIP
2007-009801	R1018	R-CHIP
2007-009805	R1013	R-CHIP
2007-009920	R312	R-CHIP

Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

2007-009969	R605	R-CHIP
2007-010233	R320	R-CHIP
2007-011511	R524	R-CHIP
2203-000233	C1014	C-CER,CHIP
2203-000233	C1015	C-CER,CHIP
2203-000233	C1119	C-CER,CHIP
2203-000233	C1123	C-CER,CHIP
2203-000386	C710	C-CER,CHIP
2203-000425	C1122	C-CER,CHIP
2203-000425	C633	C-CER,CHIP
2203-000438	C214	C-CER,CHIP
2203-000438	C707	C-CER,CHIP
2203-000489	C4099	C-CER,CHIP
2203-000489	C4100	C-CER,CHIP
2203-000725	C248	C-CER,CHIP
2203-000725	C597	C-CER,CHIP
2203-000812	C653	C-CER,CHIP
2203-000812	C654	C-CER,CHIP
2203-000812	C656	C-CER,CHIP
2203-000812	C813	C-CER,CHIP
2203-000995	C577	C-CER,CHIP
2203-000995	C580	C-CER,CHIP
2203-000995	C581	C-CER,CHIP
2203-001072	C711	C-CER,CHIP
2203-001101	C708	C-CER,CHIP
2203-001239	C632	C-CER,CHIP
2203-001383	C1016	C-CER,CHIP
2203-002677	C1093	C-CER,CHIP
2203-002687	C576	C-CER,CHIP
2203-002687	C578	C-CER,CHIP
2203-002687	C579	C-CER,CHIP
2203-005056	C1013	C-CER,CHIP
2203-005482	C563	C-CER,CHIP
2203-005682	C1003	C-CER,CHIP
2203-005682	C1092	C-CER,CHIP
2203-005682	C1107	C-CER,CHIP
2203-005682	C1108	C-CER,CHIP
2203-005682	C212	C-CER,CHIP
2203-005682	C712	C-CER,CHIP
2203-005682	C713	C-CER,CHIP
2203-005717	C1037	C-CER,CHIP
2203-005719	C1004	C-CER,CHIP
2203-005725	C201	C-CER,CHIP

Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

2203-005725	C4102	C-CER,CHIP
2203-005725	C528	C-CER,CHIP
2203-005725	C551	C-CER,CHIP
2203-005725	C715	C-CER,CHIP
2203-005725	C716	C-CER,CHIP
2203-005725	C717	C-CER,CHIP
2203-005725	C839	C-CER,CHIP
2203-005726	C275	C-CER,CHIP
2203-005727	C272	C-CER,CHIP
2203-005727	C596	C-CER,CHIP
2203-005731	C4000	C-CER,CHIP
2203-005731	C4001	C-CER,CHIP
2203-005731	C649	C-CER,CHIP
2203-005731	C651	C-CER,CHIP
2203-005734	C648	C-CER,CHIP
2203-005734	C650	C-CER,CHIP
2203-005734	C702	C-CER,CHIP
2203-005736	C1002	C-CER,CHIP
2203-005736	C1020	C-CER,CHIP
2203-005736	C1025	C-CER,CHIP
2203-005736	C1035	C-CER,CHIP
2203-005736	C1038	C-CER,CHIP
2203-005736	C1056	C-CER,CHIP
2203-005736	C1077	C-CER,CHIP
2203-005736	C1104	C-CER,CHIP
2203-005736	C1106	C-CER,CHIP
2203-005736	C1110	C-CER,CHIP
2203-005736	C1112	C-CER,CHIP
2203-005736	C211	C-CER,CHIP
2203-005736	C213	C-CER,CHIP
2203-005736	C223	C-CER,CHIP
2203-005777	C1009	C-CER,CHIP
2203-005777	C1031	C-CER,CHIP
2203-005777	C221	C-CER,CHIP
2203-005777	C228	C-CER,CHIP
2203-005777	C276	C-CER,CHIP
2203-005777	C292	C-CER,CHIP
2203-005789	C1006	C-CER,CHIP
2203-005789	C1039	C-CER,CHIP
2203-005789	C258	C-CER,CHIP
2203-005792	C1008	C-CER,CHIP
2203-005792	C1010	C-CER,CHIP
2203-005792	C1034	C-CER,CHIP

Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

2203-005792	C1109	C-CER,CHIP
2203-005792	C218	C-CER,CHIP
2203-006048	C4094	C-CER,CHIP
2203-006048	C4098	C-CER,CHIP
2203-006048	C833	C-CER,CHIP
2203-006194	C1096	C-CER,CHIP
2203-006194	C227	C-CER,CHIP
2203-006194	C291	C-CER,CHIP
2203-006194	C574	C-CER,CHIP
2203-006305	C208	C-CER,CHIP
2203-006305	C216	C-CER,CHIP
2203-006305	C225	C-CER,CHIP
2203-006305	C254	C-CER,CHIP
2203-006305	C271	C-CER,CHIP
2203-006305	C273	C-CER,CHIP
2203-006305	C277	C-CER,CHIP
2203-006305	C278	C-CER,CHIP
2203-006305	C279	C-CER,CHIP
2203-006305	C280	C-CER,CHIP
2203-006305	C281	C-CER,CHIP
2203-006305	C282	C-CER,CHIP
2203-006305	C283	C-CER,CHIP
2203-006305	C284	C-CER,CHIP
2203-006305	C285	C-CER,CHIP
2203-006305	C286	C-CER,CHIP
2203-006305	C287	C-CER,CHIP
2203-006305	C288	C-CER,CHIP
2203-006305	C289	C-CER,CHIP
2203-006305	C293	C-CER,CHIP
2203-006305	C295	C-CER,CHIP
2203-006305	C296	C-CER,CHIP
2203-006305	C719	C-CER,CHIP
2203-006399	C1021	C-CER,CHIP
2203-006399	C1022	C-CER,CHIP
2203-006399	C522	C-CER,CHIP
2203-006399	C718	C-CER,CHIP
2203-006399	C720	C-CER,CHIP
2203-006399	C721	C-CER,CHIP
2203-006399	C722	C-CER,CHIP
2203-006400	C1023	C-CER,CHIP
2203-006400	C1036	C-CER,CHIP
2203-006400	C1046	C-CER,CHIP
2203-006400	C1072	C-CER,CHIP

Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

2203-006400	C1079	C-CER,CHIP
2203-006400	C1088	C-CER,CHIP
2203-006400	C1103	C-CER,CHIP
2203-006400	C1105	C-CER,CHIP
2203-006410	C1007	C-CER,CHIP
2203-006423	C1045	C-CER,CHIP
2203-006423	C1047	C-CER,CHIP
2203-006423	C1048	C-CER,CHIP
2203-006423	C1051	C-CER,CHIP
2203-006423	C1052	C-CER,CHIP
2203-006423	C1053	C-CER,CHIP
2203-006423	C1055	C-CER,CHIP
2203-006423	C1057	C-CER,CHIP
2203-006423	C1058	C-CER,CHIP
2203-006423	C1061	C-CER,CHIP
2203-006423	C1065	C-CER,CHIP
2203-006423	C1066	C-CER,CHIP
2203-006423	C1067	C-CER,CHIP
2203-006423	C1068	C-CER,CHIP
2203-006423	C1069	C-CER,CHIP
2203-006423	C1070	C-CER,CHIP
2203-006423	C1071	C-CER,CHIP
2203-006423	C1118	C-CER,CHIP
2203-006423	C206	C-CER,CHIP
2203-006423	C238	C-CER,CHIP
2203-006423	C240	C-CER,CHIP
2203-006423	C241	C-CER,CHIP
2203-006423	C305	C-CER,CHIP
2203-006423	C306	C-CER,CHIP
2203-006423	C307	C-CER,CHIP
2203-006423	C309	C-CER,CHIP
2203-006423	C310	C-CER,CHIP
2203-006423	C312	C-CER,CHIP
2203-006423	C316	C-CER,CHIP
2203-006423	C317	C-CER,CHIP
2203-006423	C318	C-CER,CHIP
2203-006423	C319	C-CER,CHIP
2203-006423	C320	C-CER,CHIP
2203-006423	C321	C-CER,CHIP
2203-006423	C322	C-CER,CHIP
2203-006423	C323	C-CER,CHIP
2203-006423	C324	C-CER,CHIP
2203-006423	C325	C-CER,CHIP

Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

2203-006423	C326	C-CER,CHIP
2203-006423	C327	C-CER,CHIP
2203-006423	C328	C-CER,CHIP
2203-006423	C331	C-CER,CHIP
2203-006423	C332	C-CER,CHIP
2203-006423	C333	C-CER,CHIP
2203-006423	C334	C-CER,CHIP
2203-006423	C335	C-CER,CHIP
2203-006423	C338	C-CER,CHIP
2203-006423	C343	C-CER,CHIP
2203-006423	C348	C-CER,CHIP
2203-006423	C349	C-CER,CHIP
2203-006423	C351	C-CER,CHIP
2203-006423	C352	C-CER,CHIP
2203-006423	C354	C-CER,CHIP
2203-006423	C4003	C-CER,CHIP
2203-006423	C4004	C-CER,CHIP
2203-006423	C4007	C-CER,CHIP
2203-006423	C4011	C-CER,CHIP
2203-006423	C4013	C-CER,CHIP
2203-006423	C4015	C-CER,CHIP
2203-006423	C4017	C-CER,CHIP
2203-006423	C4030	C-CER,CHIP
2203-006423	C4032	C-CER,CHIP
2203-006423	C4043	C-CER,CHIP
2203-006423	C4048	C-CER,CHIP
2203-006423	C4051	C-CER,CHIP
2203-006423	C4053	C-CER,CHIP
2203-006423	C4060	C-CER,CHIP
2203-006423	C4064	C-CER,CHIP
2203-006423	C4066	C-CER,CHIP
2203-006423	C4068	C-CER,CHIP
2203-006423	C4070	C-CER,CHIP
2203-006423	C4072	C-CER,CHIP
2203-006423	C4074	C-CER,CHIP
2203-006423	C4076	C-CER,CHIP
2203-006423	C4088	C-CER,CHIP
2203-006423	C517	C-CER,CHIP
2203-006423	C518	C-CER,CHIP
2203-006423	C526	C-CER,CHIP
2203-006423	C573	C-CER,CHIP
2203-006423	C590	C-CER,CHIP
2203-006423	C609	C-CER,CHIP

Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

2203-006423	C610	C-CER,CHIP
2203-006423	C611	C-CER,CHIP
2203-006423	C612	C-CER,CHIP
2203-006423	C618	C-CER,CHIP
2203-006423	C641	C-CER,CHIP
2203-006423	C714	C-CER,CHIP
2203-006423	C817	C-CER,CHIP
2203-006423	C818	C-CER,CHIP
2203-006423	C820	C-CER,CHIP
2203-006423	C821	C-CER,CHIP
2203-006423	C823	C-CER,CHIP
2203-006423	C825	C-CER,CHIP
2203-006423	C826	C-CER,CHIP
2203-006423	C902	C-CER,CHIP
2203-006423	C903	C-CER,CHIP
2203-006423	C910	C-CER,CHIP
2203-006423	C911	C-CER,CHIP
2203-006556	C1049	C-CER,CHIP
2203-006556	C203	C-CER,CHIP
2203-006556	C357	C-CER,CHIP
2203-006556	C358	C-CER,CHIP
2203-006562	C242	C-CER,CHIP
2203-006562	C297	C-CER,CHIP
2203-006562	C562	C-CER,CHIP
2203-006562	C569	C-CER,CHIP
2203-006562	C571	C-CER,CHIP
2203-006562	C706	C-CER,CHIP
2203-006562	C831	C-CER,CHIP
2203-006562	C838	C-CER,CHIP
2203-006562	C840	C-CER,CHIP
2203-006562	C841	C-CER,CHIP
2203-006562	C908	C-CER,CHIP
2203-006562	C909	C-CER,CHIP
2203-006648	C1097	C-CER,CHIP
2203-006665	C1054	C-CER,CHIP
2203-006665	C1063	C-CER,CHIP
2203-006674	C1080	C-CER,CHIP
2203-006674	C1081	C-CER,CHIP
2203-006707	C1120	C-CER,CHIP
2203-006707	C1121	C-CER,CHIP
2203-006707	C226	C-CER,CHIP
2203-006707	C259	C-CER,CHIP
2203-006707	C260	C-CER,CHIP

Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

2203-006707	C261	C-CER,CHIP
2203-006707	C262	C-CER,CHIP
2203-006707	C267	C-CER,CHIP
2203-006707	C268	C-CER,CHIP
2203-006707	C269	C-CER,CHIP
2203-006707	C270	C-CER,CHIP
2203-006707	C290	C-CER,CHIP
2203-006824	C1078	C-CER,CHIP
2203-006824	C1095	C-CER,CHIP
2203-006824	C1098	C-CER,CHIP
2203-006824	C1101	C-CER,CHIP
2203-006824	C703	C-CER,CHIP
2203-006839	C1114	C-CER,CHIP
2203-006839	C1115	C-CER,CHIP
2203-006839	C219	C-CER,CHIP
2203-006839	C582	C-CER,CHIP
2203-006839	C583	C-CER,CHIP
2203-006839	C584	C-CER,CHIP
2203-006839	C585	C-CER,CHIP
2203-006839	C812	C-CER,CHIP
2203-006844	C572	C-CER,CHIP
2203-006872	C1042	C-CER,CHIP
2203-006872	C202	C-CER,CHIP
2203-006872	C308	C-CER,CHIP
2203-006872	C350	C-CER,CHIP
2203-006872	C353	C-CER,CHIP
2203-006872	C4005	C-CER,CHIP
2203-006872	C4041	C-CER,CHIP
2203-006872	C4046	C-CER,CHIP
2203-006872	C4050	C-CER,CHIP
2203-006872	C4089	C-CER,CHIP
2203-006872	C816	C-CER,CHIP
2203-006872	C819	C-CER,CHIP
2203-006872	C822	C-CER,CHIP
2203-006872	C824	C-CER,CHIP
2203-006896	C1089	C-CER,CHIP
2203-006896	C1090	C-CER,CHIP
2203-006896	C1091	C-CER,CHIP
2203-006979	C705	C-CER,CHIP
2203-007210	C243	C-CER,CHIP
2203-007210	C245	C-CER,CHIP
2203-007210	C246	C-CER,CHIP
2203-007210	C311	C-CER,CHIP

Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

2203-007210	C314	C-CER,CHIP
2203-007210	C315	C-CER,CHIP
2203-007210	C341	C-CER,CHIP
2203-007210	C342	C-CER,CHIP
2203-007210	C344	C-CER,CHIP
2203-007210	C345	C-CER,CHIP
2203-007210	C346	C-CER,CHIP
2203-007210	C347	C-CER,CHIP
2203-007210	C4091	C-CER,CHIP
2203-007210	C4092	C-CER,CHIP
2203-007240	C557	C-CER,CHIP
2203-007240	C564	C-CER,CHIP
2203-007240	C593	C-CER,CHIP
2203-007269	C356	C-CER,CHIP
2203-007269	C359	C-CER,CHIP
2203-007269	C829	C-CER,CHIP
2203-007269	C830	C-CER,CHIP
2203-007269	C834	C-CER,CHIP
2203-007269	C835	C-CER,CHIP
2203-007269	C836	C-CER,CHIP
2203-007269	C837	C-CER,CHIP
2203-007269	C842	C-CER,CHIP
2203-007269	C843	C-CER,CHIP
2203-007270	C1019	C-CER,CHIP
2203-007270	C567	C-CER,CHIP
2203-007270	C568	C-CER,CHIP
2203-007270	C700	C-CER,CHIP
2203-007270	C701	C-CER,CHIP
2203-007270	C814	C-CER,CHIP
2203-007270	C832	C-CER,CHIP
2203-007270	C906	C-CER,CHIP
2203-007270	C907	C-CER,CHIP
2203-007271	C200	C-CER,CHIP
2203-007271	C205	C-CER,CHIP
2203-007271	C233	C-CER,CHIP
2203-007271	C234	C-CER,CHIP
2203-007271	C301	C-CER,CHIP
2203-007271	C4093	C-CER,CHIP
2203-007271	C623	C-CER,CHIP
2203-007271	C704	C-CER,CHIP
2203-007312	C524	C-CER,CHIP
2203-007317	C251	C-CER,CHIP
2203-007317	C4040	C-CER,CHIP

Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

2203-007317	C4044	C-CER,CHIP
2203-007317	C4045	C-CER,CHIP
2203-007317	C4049	C-CER,CHIP
2203-007317	C4090	C-CER,CHIP
2203-007317	C500	C-CER,CHIP
2203-007317	C504	C-CER,CHIP
2203-007317	C505	C-CER,CHIP
2203-007317	C519	C-CER,CHIP
2203-007369	C337	C-CER,CHIP
2203-007369	C340	C-CER,CHIP
2203-007385	C4008	C-CER,CHIP
2203-007385	C4009	C-CER,CHIP
2203-007385	C4039	C-CER,CHIP
2203-007385	C904	C-CER,CHIP
2203-007385	C905	C-CER,CHIP
2203-007391	C313	C-CER,CHIP
2203-007391	C336	C-CER,CHIP
2203-007391	C355	C-CER,CHIP
2203-007391	C630	C-CER,CHIP
2203-007393	C1001	C-CER,CHIP
2203-007393	C1005	C-CER,CHIP
2203-007393	C1024	C-CER,CHIP
2203-007393	C1040	C-CER,CHIP
2203-007393	C1041	C-CER,CHIP
2203-007393	C1050	C-CER,CHIP
2203-007393	C1059	C-CER,CHIP
2203-007393	C1062	C-CER,CHIP
2203-007393	C1117	C-CER,CHIP
2203-007393	C339	C-CER,CHIP
2203-007393	C4181	C-CER,CHIP
2203-007393	C565	C-CER,CHIP
2203-007393	C566	C-CER,CHIP
2203-007393	C900	C-CER,CHIP
2203-007449	C204	C-CER,CHIP
2203-007449	C209	C-CER,CHIP
2203-007449	C247	C-CER,CHIP
2203-007449	C362	C-CER,CHIP
2203-007449	C363	C-CER,CHIP
2203-007449	C4002	C-CER,CHIP
2203-007449	C4006	C-CER,CHIP
2203-007449	C4014	C-CER,CHIP
2203-007449	C4016	C-CER,CHIP
2203-007449	C4029	C-CER,CHIP

Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

2203-007449	C4031	C-CER,CHIP
2203-007449	C4042	C-CER,CHIP
2203-007449	C4047	C-CER,CHIP
2203-007449	C4052	C-CER,CHIP
2203-007449	C4059	C-CER,CHIP
2203-007449	C4063	C-CER,CHIP
2203-007449	C4065	C-CER,CHIP
2203-007449	C4069	C-CER,CHIP
2203-007449	C4071	C-CER,CHIP
2203-007449	C4075	C-CER,CHIP
2203-007449	C4086	C-CER,CHIP
2203-007449	C4087	C-CER,CHIP
2203-007449	C4097	C-CER,CHIP
2203-007449	C4104	C-CER,CHIP
2203-007449	C4105	C-CER,CHIP
2203-007449	C4107	C-CER,CHIP
2203-007449	C4108	C-CER,CHIP
2203-007449	C4111	C-CER,CHIP
2203-007449	C4112	C-CER,CHIP
2203-007449	C4113	C-CER,CHIP
2203-007449	C4115	C-CER,CHIP
2203-007449	C4116	C-CER,CHIP
2203-007449	C4118	C-CER,CHIP
2203-007449	C4119	C-CER,CHIP
2203-007449	C4121	C-CER,CHIP
2203-007449	C4122	C-CER,CHIP
2203-007449	C4124	C-CER,CHIP
2203-007449	C4125	C-CER,CHIP
2203-007449	C4127	C-CER,CHIP
2203-007449	C4128	C-CER,CHIP
2203-007449	C4130	C-CER,CHIP
2203-007449	C4131	C-CER,CHIP
2203-007449	C4133	C-CER,CHIP
2203-007449	C4134	C-CER,CHIP
2203-007449	C4136	C-CER,CHIP
2203-007449	C4137	C-CER,CHIP
2203-007449	C4139	C-CER,CHIP
2203-007449	C4140	C-CER,CHIP
2203-007449	C4142	C-CER,CHIP
2203-007449	C4143	C-CER,CHIP
2203-007449	C4146	C-CER,CHIP
2203-007449	C4147	C-CER,CHIP
2203-007449	C4149	C-CER,CHIP

Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

2203-007449	C4150	C-CER,CHIP
2203-007449	C4152	C-CER,CHIP
2203-007449	C4153	C-CER,CHIP
2203-007449	C4155	C-CER,CHIP
2203-007449	C4156	C-CER,CHIP
2203-007449	C4158	C-CER,CHIP
2203-007449	C4159	C-CER,CHIP
2203-007449	C4161	C-CER,CHIP
2203-007449	C4162	C-CER,CHIP
2203-007449	C4164	C-CER,CHIP
2203-007449	C4165	C-CER,CHIP
2203-007449	C4167	C-CER,CHIP
2203-007449	C4168	C-CER,CHIP
2203-007449	C4170	C-CER,CHIP
2203-007449	C4171	C-CER,CHIP
2203-007449	C4173	C-CER,CHIP
2203-007449	C4174	C-CER,CHIP
2203-007449	C4176	C-CER,CHIP
2203-007449	C4177	C-CER,CHIP
2203-007449	C4179	C-CER,CHIP
2203-007449	C4180	C-CER,CHIP
2203-007449	C4182	C-CER,CHIP
2203-007449	C5000	C-CER,CHIP
2203-007449	C529	C-CER,CHIP
2203-007449	C530	C-CER,CHIP
2203-007449	C533	C-CER,CHIP
2203-007449	C534	C-CER,CHIP
2203-007449	C535	C-CER,CHIP
2203-007449	C536	C-CER,CHIP
2203-007449	C537	C-CER,CHIP
2203-007449	C538	C-CER,CHIP
2203-007449	C539	C-CER,CHIP
2203-007449	C541	C-CER,CHIP
2203-007449	C543	C-CER,CHIP
2203-007449	C545	C-CER,CHIP
2203-007449	C546	C-CER,CHIP
2203-007449	C547	C-CER,CHIP
2203-007449	C549	C-CER,CHIP
2203-007449	C589	C-CER,CHIP
2203-007449	C594	C-CER,CHIP
2203-007449	C607	C-CER,CHIP
2203-007449	C620	C-CER,CHIP
2203-007449	C621	C-CER,CHIP

Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

2203-007449	C638	C-CER,CHIP
2203-007449	C801	C-CER,CHIP
2203-007449	C804	C-CER,CHIP
2203-007449	C806	C-CER,CHIP
2203-007449	C807	C-CER,CHIP
2203-007449	C809	C-CER,CHIP
2203-007449	C901	C-CER,CHIP
2203-007474	C302	C-CER,CHIP
2203-007474	C303	C-CER,CHIP
2203-007474	C304	C-CER,CHIP
2203-007474	C501	C-CER,CHIP
2203-007474	C502	C-CER,CHIP
2203-007474	C503	C-CER,CHIP
2203-007474	C506	C-CER,CHIP
2203-007474	C507	C-CER,CHIP
2203-007474	C508	C-CER,CHIP
2203-007474	C509	C-CER,CHIP
2203-007474	C514	C-CER,CHIP
2203-007474	C520	C-CER,CHIP
2203-007474	C521	C-CER,CHIP
2203-007474	C554	C-CER,CHIP
2203-007474	C555	C-CER,CHIP
2203-007474	C558	C-CER,CHIP
2203-007474	C815	C-CER,CHIP
2203-007775	C229	C-CER,CHIP
2203-007775	C230	C-CER,CHIP
2203-007775	C231	C-CER,CHIP
2203-007775	C239	C-CER,CHIP
2203-007775	C249	C-CER,CHIP
2203-007781	C552	C-CER,CHIP
2203-007781	C559	C-CER,CHIP
2203-007781	C575	C-CER,CHIP
2203-007795	C360	C-CER,CHIP
2203-007796	C207	C-CER,CHIP
2203-007796	C232	C-CER,CHIP
2203-007796	C235	C-CER,CHIP
2203-007796	C236	C-CER,CHIP
2203-007796	C237	C-CER,CHIP
2203-007796	C244	C-CER,CHIP
2203-007796	C629	C-CER,CHIP
2203-007796	C637	C-CER,CHIP
2203-007796	C800	C-CER,CHIP
2203-007796	C802	C-CER,CHIP

Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

2203-007796	C803	C-CER,CHIP
2203-007796	C912	C-CER,CHIP
2203-008095	C1060	C-CER,CHIP
2203-008097	C294	C-CER,CHIP
2203-008123	C595	C-CER,CHIP
2203-008126	C587	C-CER,CHIP
2203-008126	C588	C-CER,CHIP
2203-008126	C598	C-CER,CHIP
2203-008176	C586	C-CER,CHIP
2203-008199	C553	C-CER,CHIP
2203-008199	C556	C-CER,CHIP
2203-008217	C298	C-CER,CHIP
2203-008217	C5001	C-CER,CHIP
2203-008217	C570	C-CER,CHIP
2203-008242	C4010	C-CER,CHIP
2203-008242	C4012	C-CER,CHIP
2203-008242	C4058	C-CER,CHIP
2203-008242	C4067	C-CER,CHIP
2203-008242	C4073	C-CER,CHIP
2203-008242	C4103	C-CER,CHIP
2203-008242	C4106	C-CER,CHIP
2203-008242	C4109	C-CER,CHIP
2203-008242	C4110	C-CER,CHIP
2203-008242	C4114	C-CER,CHIP
2203-008242	C4117	C-CER,CHIP
2203-008242	C4120	C-CER,CHIP
2203-008242	C4123	C-CER,CHIP
2203-008242	C4126	C-CER,CHIP
2203-008242	C4129	C-CER,CHIP
2203-008242	C4132	C-CER,CHIP
2203-008242	C4135	C-CER,CHIP
2203-008242	C4138	C-CER,CHIP
2203-008242	C4141	C-CER,CHIP
2203-008242	C4145	C-CER,CHIP
2203-008242	C4148	C-CER,CHIP
2203-008242	C4151	C-CER,CHIP
2203-008242	C4154	C-CER,CHIP
2203-008242	C4157	C-CER,CHIP
2203-008242	C4160	C-CER,CHIP
2203-008242	C4163	C-CER,CHIP
2203-008242	C4166	C-CER,CHIP
2203-008242	C4169	C-CER,CHIP
2203-008242	C4172	C-CER,CHIP

Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

2203-008242	C4175	C-CER,CHIP
2203-008242	C4178	C-CER,CHIP
2203-008242	C515	C-CER,CHIP
2203-008242	C516	C-CER,CHIP
2203-008242	C531	C-CER,CHIP
2203-008242	C532	C-CER,CHIP
2203-008242	C540	C-CER,CHIP
2203-008242	C542	C-CER,CHIP
2203-008242	C544	C-CER,CHIP
2203-008242	C548	C-CER,CHIP
2203-008242	C550	C-CER,CHIP
2203-008243	C527	C-CER,CHIP
2203-008394	C1073	C-CER,CHIP
2203-008394	C210	C-CER,CHIP
2203-008394	C215	C-CER,CHIP
2203-008394	C222	C-CER,CHIP
2203-008394	C224	C-CER,CHIP
2203-008394	C250	C-CER,CHIP
2203-008394	C252	C-CER,CHIP
2203-008394	C253	C-CER,CHIP
2203-008394	C255	C-CER,CHIP
2203-008394	C256	C-CER,CHIP
2203-008394	C263	C-CER,CHIP
2203-008394	C264	C-CER,CHIP
2203-008394	C265	C-CER,CHIP
2203-008394	C266	C-CER,CHIP
2203-008529	C605	C-CER,CHIP
2203-008529	C606	C-CER,CHIP
2203-008529	C608	C-CER,CHIP
2203-008529	C615	C-CER,CHIP
2203-008529	C616	C-CER,CHIP
2203-008529	C624	C-CER,CHIP
2203-008529	C625	C-CER,CHIP
2203-008529	C635	C-CER,CHIP
2203-008691	C914	C-CER,CHIP
2203-008691	C915	C-CER,CHIP
2203-008691	C916	C-CER,CHIP
2203-008876	C709	C-CER,CHIP
2203-008885	C5003	C-CER,CHIP
2203-008885	C510	C-CER,CHIP
2203-008885	C511	C-CER,CHIP
2203-008885	C512	C-CER,CHIP
2203-008885	C513	C-CER,CHIP

Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

2203-008885	C523	C-CER,CHIP
2203-008885	C525	C-CER,CHIP
2203-008885	C560	C-CER,CHIP
2203-008885	C561	C-CER,CHIP
2404-001516	TA600	C-TA,CHIP
2703-001178	L1009	INDUCTOR-SMD
2703-002205	L1041	INDUCTOR-SMD
2703-002208	L1070	INDUCTOR-SMD
2703-002309	L605	INDUCTOR-SMD
2703-002309	L606	INDUCTOR-SMD
2703-002309	L607	INDUCTOR-SMD
2703-002309	L608	INDUCTOR-SMD
2703-002309	L609	INDUCTOR-SMD
2703-002313	L1010	INDUCTOR-SMD
2703-002313	L1065	INDUCTOR-SMD
2703-002314	L1011	INDUCTOR-SMD
2703-002367	L202	INDUCTOR-SMD
2703-002367	L232	INDUCTOR-SMD
2703-002369	L1072	INDUCTOR-SMD
2703-002596	L1013	INDUCTOR-SMD
2703-002649	L208	INDUCTOR-SMD
2703-002951	L1044	INDUCTOR-SMD
2703-002951	L1046	INDUCTOR-SMD
2703-002958	L1042	INDUCTOR-SMD
2703-002999	L1058	INDUCTOR-SMD
2703-003121	L1071	INDUCTOR-SMD
2703-003260	L1036	INDUCTOR-SMD
2703-003545	L217	INDUCTOR-SMD
2703-003755	L1001	INDUCTOR-SMD
2703-003755	L1007	INDUCTOR-SMD
2703-003755	L1031	INDUCTOR-SMD
2703-003781	L610	INDUCTOR-SMD
2703-003781	L611	INDUCTOR-SMD
2703-003873	L301	INDUCTOR-SMD
2703-003873	L302	INDUCTOR-SMD
2703-003873	L303	INDUCTOR-SMD
2703-004000	L1052	INDUCTOR-SMD
2703-004000	L1059	INDUCTOR-SMD
2703-004012	L1012	INDUCTOR-SMD
2703-004012	L1014	INDUCTOR-SMD
2703-004012	L1019	INDUCTOR-SMD
2703-004018	L1034	INDUCTOR-SMD
2703-004018	L1060	INDUCTOR-SMD

Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

2703-004030	L201	INDUCTOR-SMD
2703-004032	L1002	INDUCTOR-SMD
2703-004032	L1016	INDUCTOR-SMD
2703-004032	L1025	INDUCTOR-SMD
2703-004032	L1055	INDUCTOR-SMD
2703-004032	L1057	INDUCTOR-SMD
2703-004032	L1066	INDUCTOR-SMD
2703-004032	L206	INDUCTOR-SMD
2703-004032	L220	INDUCTOR-SMD
2703-004034	L1035	INDUCTOR-SMD
2703-004034	L245	INDUCTOR-SMD
2703-004035	L1017	INDUCTOR-SMD
2703-004035	L1074	INDUCTOR-SMD
2703-004035	L204	INDUCTOR-SMD
2703-004035	L230	INDUCTOR-SMD
2703-004035	L231	INDUCTOR-SMD
2703-004036	L1023	INDUCTOR-SMD
2703-004036	L1028	INDUCTOR-SMD
2703-004037	L1073	INDUCTOR-SMD
2703-004038	L1030	INDUCTOR-SMD
2703-004038	L213	INDUCTOR-SMD
2703-004038	L236	INDUCTOR-SMD
2703-004231	L800	INDUCTOR-SMD
2703-004249	L804	INDUCTOR-SMD
2703-004249	L806	INDUCTOR-SMD
2703-004295	L1015	INDUCTOR-SMD
2703-004295	L1048	INDUCTOR-SMD
2703-004299	L1003	INDUCTOR-SMD
2703-004300	L246	INDUCTOR-SMD
2703-004301	L1047	INDUCTOR-SMD
2703-004301	L1049	INDUCTOR-SMD
2703-004302	L1051	INDUCTOR-SMD
2703-004302	L1053	INDUCTOR-SMD
2703-004302	L1064	INDUCTOR-SMD
2703-004302	L1067	INDUCTOR-SMD
2703-004328	L1038	INDUCTOR-SMD
2703-004328	L1054	INDUCTOR-SMD
2703-004362	L1008	INDUCTOR-SMD
2703-004363	L1005	INDUCTOR-SMD
2703-004366	L1056	INDUCTOR-SMD
2703-004366	L1062	INDUCTOR-SMD
2703-004367	L200	INDUCTOR-SMD
2703-004371	L1024	INDUCTOR-SMD

Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

2703-004371	L1040	INDUCTOR-SMD
2703-004371	L1050	INDUCTOR-SMD
2703-004554	L513	INDUCTOR-SMD
2703-004775	L500	INDUCTOR-SMD
2703-004775	L501	INDUCTOR-SMD
2703-004775	L503	INDUCTOR-SMD
2703-004775	L504	INDUCTOR-SMD
2703-004775	L506	INDUCTOR-SMD
2703-004775	L507	INDUCTOR-SMD
2703-004775	L509	INDUCTOR-SMD
2703-004775	L512	INDUCTOR-SMD
2703-004901	L502	INDUCTOR-SMD
2703-004901	L505	INDUCTOR-SMD
2703-004901	L508	INDUCTOR-SMD
2703-004901	L510	INDUCTOR-SMD
2703-004901	L511	INDUCTOR-SMD
2703-004976	L1027	INDUCTOR-SMD
2703-005058	L1068	INDUCTOR-SMD
2801-005051	OSC200	CRYSTAL-SMD
2801-005163	OSC4000	CRYSTAL-SMD
2801-005319	OSC500	OSCILLATOR-TCXO
2805-001106	OSC201	OSCILLATOR-TCXO
2809-001376	OSC1001	OSCILLATOR-VCTCXO
2901-001625	F700	FILTER-EMI/ESD
2901-001625	F800	FILTER-EMI/ESD
2901-001625	F803	FILTER-EMI/ESD
2901-001647	F801	FILTER-EMI SMD
2901-001647	F802	FILTER-EMI SMD
2901-001647	F804	FILTER-EMI SMD
2901-001690	C329	FILTER-EMI SMD
2901-001690	C330	FILTER-EMI SMD
2901-001743	F805	FILTER-EMI/ESD
2901-001743	F806	FILTER-EMI/ESD
2901-001743	F807	FILTER-EMI/ESD
2901-001743	F808	FILTER-EMI/ESD
2901-001743	F809	FILTER-EMI/ESD
2904-002015	F1004	FILTER-SAW
2904-002020	F1005	FILTER-SAW
2904-002024	F1008	FILTER-SAW
2904-002091	F1006	FILTER-SAW
2904-002133	F201	FILTER-SAW
2904-002133	F206	FILTER-SAW
2904-002145	F1007	FILTER-SAW

Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

2904-002168	F200	FILTER-GPS SAW
2904-002168	F202	FILTER-GPS SAW
2910-000223	U1001	DUPLEXER-SAW
2910-000224	F1003	DUPLEXER-SAW
2910-000256	F1002	DUPLEXER-SAW
2911-000267	U1008	DUPLEXER-ASM
2911-000268	U1002	DUPLEXER-ASM
2911-000294	F203	DUPLEXER-FEM
2911-000294	F207	DUPLEXER-FEM
2911-000295	F205	DUPLEXER-FEM
2911-000295	F209	DUPLEXER-FEM
3301-001789	L805	BEAD-SMD
3301-001820	L702	BEAD-SMD
3301-001820	L703	BEAD-SMD
3301-001851	L807	BEAD-SMD
3301-001851	L808	BEAD-SMD
3301-001885	L612	BEAD-SMD
3301-001895	L203	BEAD-SMD
3301-001895	L238	BEAD-SMD
3301-001895	L239	BEAD-SMD
3301-001956	L1026	BEAD-SMD
3301-002065	L602	BEAD-SMD
3301-002078	L603	BEAD-SMD
3301-002078	L604	BEAD-SMD
3301-002122	L1033	BEAD-SMD
3301-002228	L601	BEAD-SMD
3301-002237	L802	BEAD-SMD
3301-002237	L803	BEAD-SMD
3705-001731	RFS1001	CONNECTOR-COAXIAL
3708-003131	SCL800	CONNECTOR-FPC/FFC/PIC
3708-003187	HEA700	CONNECTOR-FPC/FFC/PIC
3711-006852	HDC600	HEADER-BOARD TO BOARD
3711-006925	HEA801	HEADER-BOARD TO BOARD
3711-007295	HEA800	HEADER-BOARD TO BOARD
3711-007467	HEA4000	HEADER-BOARD TO BOARD
3711-007478	HDC900	HEADER-BOARD TO BOARD
3711-008421	BTC500	CONNECTOR-HEADER
3712-001490	ANT100	CONNECTOR-TERMINAL
3712-001490	ANT101	CONNECTOR-TERMINAL
3712-001490	ANT102	CONNECTOR-TERMINAL
3712-001490	ANT103	CONNECTOR-TERMINAL
3712-001490	ANT200	CONNECTOR-TERMINAL
3712-001490	ANT201	CONNECTOR-TERMINAL

Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

3712-001490	ANT202	CONNECTOR-TERMINAL
3712-001490	ANT203	CONNECTOR-TERMINAL
3712-001493	ANT600	CONNECTOR-TERMINAL
3712-001493	ANT601	CONNECTOR-TERMINAL
3712-001493	ANT602	CONNECTOR-TERMINAL
3712-001493	ANT603	CONNECTOR-TERMINAL
4709-001672	CPL200	FREQ-DISTRIBUTER
4709-002028	F204	FREQ-DISTRIBUTER
4709-002028	F208	FREQ-DISTRIBUTER
4709-002178	F1001	COUPLER-DIRECTION
GH62-00034A	CON800	PAD GAP-SMD GASKET(SM_T230)
GH80-03320A	R302	SOLDER-CREAM/SMT KOREA(FREE)
GH80-03320A	R4116	SOLDER-CREAM/SMT KOREA(FREE)
GH98-31347A	SC102	ASSY COVER-SHIELD COVER A
GH98-31349A	SC103	ASSY COVER-SHIELD COVER C
GH98-31350A	SC101	ASSY COVER-SHIELD COVER D
GH98-31942A	SC104	ASSY COVER-SHIELD FRAME B

Please consult the GSPN website (Samsung Portal) for the most recent version of the product's part list.

Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

6. Level 1 Repair

6-1. S/W installation

6-1-1. Required items in order to install S/W

- Installation program: Downloader Program (**Odin3 v3.09.3.exe**)
- SM-T805 Galaxy Tab S
- Data Cable (GH39-01661A)
- JIG BOX (GH99-36900B)
- JIG Cable (GH81-10623A)
- Adapter (GH99-38251A)
- Serial Cable
- Mobile device specific S/W: Binary files

※ Settings

Connect ANYWAY JIG BOX
with JIG CABLE (Phone to JIG)
or PC to Phone Using Data Cable

Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

6-1-2. S/W Installation Program (Downloader program)

■ Open up the S/W Installation Program by executing the "**Odin3 v3.09.3.exe**"



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

1. Enable the check mark by click on the following options,

- Check Auto Reboot, Re-Partition, and F. Reset Time
- Check PIT
- Check BL, AP, CP, and CSC Files

  * Note : "Odin v3.09 or above" checks MD5 checksum just after file selection.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

2. Enter into Download Mode

Enter into Download Mode by pressing Home button ,Volume Down button and Power Button simultaneously followed by pressing Volume up button as a direction of the phone.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

3. Connect the device to PC via Data Cable.

Make sure that the one of communication ports [ID:COM] box is highlighted in sky blue. The device is now connected with the PC and ready to download the binary files in it.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

4. Start downloading the binary files into the device by clicking Start button on the screen. The green colored "PASS!" sign will appear on the upper-left box if the binary files have been successfully downloaded into the device.



5. Disconnect the device from the Data cable.

6. Once the device boots up, you can check the version of the binary file or name by pressing the following code in sequence;

***#1234#**

You can perform Factory Reset by Settings → Accounts → Backup and reset

Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

7. Level 2 Repair

7-1. Disassembly and Assembly Instructions

7-1-1. Disassembly

1 Disjoint Hook at REAR // Disassemble REAR	
 STEP 1,2,3 → 4,5	 SM-T800_5 disassemble tool
1) Be careful not to make scratch and molding damage!	1) Use Band point of disassembly jig
2 Remove the screw(9EA)	3 Disconnect the connector and tape
 Red point(2EA) : Black screw Green point(7EA) : Silver screw	 GREEN: Connector RED : be careful not to crack FPCB(both sides tape)
Be careful, use of different screws	Be careful, do not damage FPCB connector

Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

4 Disassemble SPK(L),(R)	5 Remove the battery
	
Be careful, do not damage FPCB	Be careful, do not damage Battery
6 Remove the PBA	
	
Be careful, do not damage FPCB	

Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

7-1-2. Assembly

1 Assemble PBA 	2 Assemble the battery 
Be careful, do not damage FPCB	Be careful, do not damage Battery
3 Assemble SPK(L),(R) 	4 Assemble the MIC/USB/SIM FPCB 
Be careful, do not damage FPCB Check Ear-jack SUS	Be careful, do not damage FPCB

Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

5 Assemble the connector & tape	6 tightening the IF screws(2EA)
	 Red point(2EA) : Black screw
Be careful, do not damage FPCB connector	● Torque : 1.1 ~ 1.3 Kgf · cm / ● Size : 1.4 * 4 (6001-001479)
7 tightening the screws(7EA)	8 Assemble Rear
 Green point(7EA) : Silver screw	  Assembly STEP 1 ~ 14
● Torque : 1.1 ~ 1.3 Kgf · cm / ● Size : 1.4 * 3 (6001-001811)	Be careful, do not assemble hook

Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

8. Level 3 Repair

8-1. Block Diagram



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

8-2. PCB Diagrams

8-2-1. Main PCB Top



8-2-2. Bottom



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

8-3. Flow Chart of Troubleshooting

Equipments



↑ Oscilloscope

↑ Digital Multimeter

↑ Power Supply

↑ + driver, ESD Safe Tweezer



↑ 8960 & Spectrum Analyzer

↑ Soldering iron

Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

8-3-1. Power On



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.







Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

8-3-2. Initial



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.


U500
SC1104
UCP4001
OSC4000
C4039
R4001
R4007
R4003
R4006
C4045
TR501
R4201
R4077
R4024
R4035
C4041
R4026
R4037
R4023
R4034
R801
UME4000
C554
C557
C556
C558
C559
C560
C561
C562
C563
C564
C565
C566
C567
C568
C569
C570
C571
C572
C573
C574
C575
C576
C577
C578
C579
C580
C581
C582
C583
C584
C585
C586
C587
C588
C589
C590
C591
C592
C593
C594
C595
C596
C597

8-3-3. No Service



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.





Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

8-3-4. Charging Part



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.





Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.





Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

8-3-5 Microphone Part



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.


CON800
LED500
UME4000
UCP4001
U502
U700
U701
U702
U804
U500
SC4104
ZD700
C703
C559
C552
L508
L507
L506
L502
L503
L504
L500
L505
L512
L501
L510
L511
L509
C557
C554
C553
C558
C555
C556
C551
C550
R700
R701
R702
R703
Q700
Q701
Q702
Q703
Q704
Q705
Q706
Q707
Q708
Q709
Q710
Q711
Q712
Q713
Q714
Q715
Q716
Q717
Q718
Q719
Q720
Q721
Q722
Q723
ZD800
ZD801
ZD802
ZD803
ZD804
ZD805
ZD806
ZD807
ZD808
ZD809
ZD810
ZD811
ZD812
ZD813
ZD814
ZD815
ZD816
ZD817
ZD818
ZD819
ZD820
ZD821
ZD822
ZD823
ZD824
ZD825
ZD826
ZD827
ZD828
ZD829
ZD830
ZD831
ZD832
ZD833
ZD834
ZD835
ZD836
ZD837
ZD838
ZD839

8-3-6-1. Speaker Part (LEFT)



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



CODEC



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

8-3-6-2. Speaker Part (RIGHT)



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



CODEC



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

8-3-7. BT



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.







Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

8-3-8. WIFI



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.





Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.





Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

8-3-9. GPS



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.









Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

8-3-10. LCD



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

8-3-11. TSP



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

8-3-12. VT CAM



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.







Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

8-3-13. 8M CAM



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.







Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

8-3-13. OTG



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

8-3-14. MHL



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.





Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.





Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

8-3-16. Sim Part



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.







Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

8-3-17. Motor



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.







Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

8-3-18. Fingerprint



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.







Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

8-3-19. GSM1800 RX



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

8-3-20. LTE Band1/ WCDMA Band1 RX

CONTINUOUS RX ON

WCDMA1 CH : 10700
LTE B1 CH : 300

AMP : -50dBm



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

8-3-21. WCDMA Band2 RX



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.


ANT100
ANT101
RFS1001
PAM1001
PAM1002
F1003
U1001
U1002
U1007
F1004
F1006
F1007
F1005
F1008
U1008
OSC1001
L1031
L1026
L1001
L1007
C1019
C1041
C1050
C1042
C1117
L1013
C1001
C1024
C1040
C1046
C1047
C1054
C1055
C1035
C1062
C1063
C1064
C1065
C1066
C1068
C1069
C1070
C1071
C1072
C1073
C1074
C1075
C1076
C1077
C1078
C1079
C1080
C1081
C1082
C1083
C1084
C1085
C1086
C1087
C1088
C1089
C1090
C1091
C1092
C1093
C1094
C1095
C1096
C1097
C1098
C1099
C1100
C1101
C1102
C1103
C1104
C1105
C1106
C1107
C1108
C1109
C1110
C1111
C1112
C1113
C1114
C1115
C1116
C1117
C1118
C1119
C1120
C1121
C1122
L1001
L1002
L1003
L1004
L1005
L1006
L1007
L1008
L1009
L1010
L1011
L1012
L1013
L1014
L1015
L1016
L1017
L1018
L1019
L1020
L1021
L1022
L1023
L1024
L1025
L1026
L1027
L1028
L1029
L1030
L1031
L1032
L1033
L1034
L1035
L1036
L1037
L1038
L1039
L1040
L1041
L1042
L1043
L1044
L1045
L1046
L1047
L1048
L1049
L1050
L1051
L1052
L1053
L1054
L1055
L1056
L1057
L1058
L1059
L1060
L1061
L1062
L1063
L1064
L1065
L1066
L1067
L1068
L1069
L1070
L1071
R1001
R1002
R1003
R1004
R1005
R1006
R1007
R1008
R1009
R1010
R1011
R1012
R1013
R1014
R1015
R1016
R1017
R1018
R1019
R1020
R1021
R1022
R1023
R1024
R1025
R1026
R1027
R1028
R1029
R1030
R1031
R1032
R1033
R1034
R1035
R1036
R1037
R1038
R1039
R1040

8-3-22. LTE Band3 RX

CONTINUOUS RX ON
RF INPUT : 1575CH
AMP : -50dBm



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

8-3-23. LTE Band5 / WCDMA Band5 / GSM850 RX

CONTINUOUS RX ON

WCDMA5 CH : 4408
LTE B5 CH : 2525

AMP : -50dBm



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

8-3-24. LTE Band7 RX

CONTINUOUS RX ON
RF INPUT : 3100CH
AMP : -50dBm



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

8-3-25. LTE Band8 / WCDMA Band8 / GSM900 RX

CONTINUOUS RX ON

WCDMA8 CH : 3013
LTE B8 CH : 3625

AMP : -50dBm



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

8-3-26. LTE Band20 RX

CONTINUOUS RX ON
RF INPUT : 6300CH
AMP : -50dBm



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.







Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

8-3-27. GSM850 / GSM900 TX

CONTINOUS TX ON CONDITION
TX POWER DAC:14500 CODE APPLIED
GSM850 CH : 190
GSM900 CH : 62
RBW : 100KHz
VBW : 100KHz
SPAN : 10MHz
REF LEV. : 10dBm
ATT. : 20dB



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

8-3-28. DCS/ PCS TX

CONTINOUS TX ON CONDITION
TX POWER DAC:14500 CODE APPLIED
DCS CH : 685
PCS CH : 661
RBW : 100KHz
VBW : 100KHz
SPAN : 10MHz
REF LEV. : 10dBm
ATT. : 20dB



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

8-3-28. WCDMA Band1 TX

CONTINOUS TX ON CONDITION
TX POWER DAC:14500 CODE APPLIED
WCDMA Band1 CH : 9750
RBW : 100KHz
VBW : 100KHz
SPAN : 10MHz
REF LEV. : 10dBm
ATT. : 20dB



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.


ANT100
ANT101
RFS1001
PAM1001
PAM1002
U1001
U1002
U1007
U1008
OSC1001
UCP301
U1003
U1010
U1904
U903
U302
U701
OSC500
L512
L50
L1036
L303
L302
L301
C359
C356
C303
C304
C360
C340
C363
C301
C706
C708
C707
C912
C914
C918
C916
R703
R701
R506
R507
R505
R508
R509
R320
R316
R315
R314
C523
C525
C524
C551
C561
C528
C542
C541
C532
C533
C534
C535
C536
C537
C538
C539
C540
C543
C544
C545
C546
C547
C548
C549
C550
C1094
C1093
C1098
C1101
C1095
C1078
C1021
C1022
R1004
R1005
C1116
R1024
C1033
C1079
R1010
C310
C311
C313
C337
C348
C1041
C1050
C1131
C1013
C1117
C1042
C1026
C1001
C1004
C1016
C1019
L1007
L1026
L1027
L1031
F1002
F1003
F1004
F1005
F1006
F1007
F1008
F1009
L1070
C1122
C1014
L1009
C1013
L1071
R1025
L1065
L1011
C1018
C1044
C1043
C1075
C1076
C1077
C1078
C1079
C1080
C1081
C1082
C1083
C1084
C1085
C1086
C1087
C1088
C1089
C1090
C1091
C1092
C1095
C1096
C1097
C1098
C1099
C1100
C1101
C1102
C1103
C1104
C1105
C1106
C1107
C1108
C1109
C1110
C1111
C1112
C1113
C1114
C1115
C1116
C1117
C1118
C1119
C1120
C1121
C1122
C1123
C1124
C1125
C1126
C1127
C1128
C1129
C1130
C1131
C1132
C1133
C1134

8-3-28. WCDMA Band2 TX

CONTINOUS TX ON CONDITION
TX POWER DAC:14500 CODE APPLIED
WCDMA Band2 CH : 9400
RBW : 100KHz
VBW : 100KHz
SPAN : 10MHz
REF LEV. : 10dBm
ATT. : 20dB



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

8-3-28. WCDMA Band5 TX



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

8-3-28. WCDMA Band8 TX

CONTINOUS TX ON CONDITION
TX POWER DAC:14500 CODE APPLIED
WCDMA Band900 CH : 2788
RBW : 100KHz
VBW : 100KHz
SPAN : 10MHz
REF LEV. : 10dBm
ATT. : 20dB



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

8-3-28. LTE Band1 TX

CONTINOUS TX ON CONDITION
TX POWER DAC:14500 CODE APPLIED
LTE Band1 CH : 18300
RBW : 100KHz
VBW : 100KHz
SPAN : 10MHz
REF LEV. : 10dBm
ATT. : 20dB



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

8-3-28. LTE Band3 TX

CONTINUOUS TX ON CONDITION
APPLIED
LTE Band3 CH : 19575
RBW : 100KHz
VBW : 100KHz
SPAN : 10MHz
REF LEV. : 10dBm
ATT. : 20dB



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

8-3-28. LTE Band5 TX



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

8-3-28. LTE Band7 TX

CONTINUOUS TX ON CONDITION APPLIED
LTE Band7 CH : 21100
RBW : 100KHz
VBW : 100KHz
SPAN : 10MHz
REF LEV. : 10dBm
ATT. : 20dB



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

8-3-28. LTE Band8 TX

CONTINOUS TX ON CONDITION
TX POWER DAC:14500 CODE APPLIED
LTE Band8 CH : 21625
RBW : 100KHz
VBW : 100KHz
SPAN : 10MHz
REF LEV. : 10dBm
ATT. : 20dB



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

8-3-28. LTE Band20 TX

CONTINUOUS TX ON CONDITION
APPLIED
LTE Band20 CH : 24300
RBW : 100KHz
VBW : 100KHz
SPAN : 10MHz
REF LEV. : 10dBm
ATT. : 20dB



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

8-3-24. LTE Band1 / WCDMA Band1 DRX

CONTINUOUS RX ON
RF INPUT : LTE B1: 300CH
WCDMA B1: 10700CH
AMP : -50dBm



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

8-3-24. WCDMA Band2 DRX

CONTINUOUS RX ON
RF INPUT : WCDMA B2:
9800CH
AMP : -50dBm



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

8-3-24. LTE Band3 DRX

CONTINUOUS RX ON
RF INPUT : LTE B3: 1575CH
AMP : -50dBm



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.





Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

8-3-24. LTE Band20 DRX

CONTINUOUS RX ON
RF INPUT : LTE B20: 6300CH
AMP : -50dBm



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.



Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

9. Reference Abbreviate

Reference Abbreviate

- **AAC**: Advanced Audio Coding.
- **AVC** : Advanced Video Coding.
- **BER** : Bit Error Rate
- **BPSK**: Binary Phase Shift Keying
- **CA** : Conditional Access
- **CDM** : Code Division Multiplexing
- **C/I** : Carrier to Interference
- **DMB** : Digital Multimedia Broadcasting
- **EN** : European Standard
- **ES** : Elementary Stream
- **ETSI**: European Telecommunications Standards Institute
- **MPEG**: Moving Picture Experts Group
- **PN** : Pseudo-random Noise
- **PS** : Pilot Symbol
- **QPSK**: Quadrature Phase Shift Keying
- **RS** : Reed-Solomon
- **SI** : Service Information
- **TDM** : Time Division Multiplexing
- **TS** : Transport Stream

Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without Samsung's written authorization is strictly prohibited.

SAMSUNG
ELECTRONICS

This Service Manual is a property of Samsung Electronics Co.,Ltd.
Any unauthorized use of Manual can be punished under applicable International and/or domestic law.

© Samsung Electronics Co.,Ltd.

2014. 05. Rev.1.0

www.s-manuals.com